

FTE WAVE

1. Press the **HOME** or **MENU** button on the remote control
2. Go to **Settings**
3. Go to **Factory Settings**
4. Type in **0-0-0-0** for the password
5. Select **YES** once “*This operation will load default settings and erase all the channels, continue?*” message appears
6. Click the **NEXT** option until you reach the screen where it will show you the following options below. Then change the settings accordingly.
 - 6.1 – Antenna Configuration <Fixed Antenna> *(Default setting so no need to change)*
 - 6.2 – Auto Satellite Configuration set **ON**
 - 6.3 – Go to **Antenna Setup**, make sure there is a check mark (✓) on **Badr 4/5/6**
 - 6.4 – Click the **EXIT** button on the remote to commence auto configuration on the receiver
 - 6.5 – Go to **Channel Search** to commence automatic scanning
7. Once scanning is done, a “*Search Completed*” message will appear on the screen
8. Click **OK** to save the channels
9. Scroll down and select the **Finished!** option, and click **OK** on the remote control
10. Click the **MYHD** button on the remote control, and select your subscription channel list accordingly to view all the channels

CAMBRIDGE 1.0/TRUVIEW 7 MATRIX/GALAXIS 99/G-GUARD

1. Press **MENU** button on the remote control
2. Go to **Installation**
3. Type in the pin code **0-0-0-0**, and then click **OK** on the remote
4. Select **Satellite Management**, and then click **OK** on the remote
5. Make sure satellite is set to **BADR 4-6/Eshail 1**. If not, press the right arrow key and look for **BADR 4-6/Eshail 1**
6. Scroll down the list, and select the frequency **11823, 27500, V** *(This frequency will allow you to get all My-HD Channels)*
7. Click the **blue** button (*Search*) on the remote control and set the following:
 - 7.1 – **Frequency** set to **11823** *(Default setting so no need to change)*
 - 7.2 – **NIT Search** set to **ON**
 - 7.3 – **FTA Only** set to **No** *(Default setting so no need to change)*
8. Go to the **OK** option below, and click the **OK** button on the remote control to commence the scanning process
9. Click the **OK** button on the remote control once “*Scanning finished. Press OK to save...*” message appears on the TV screen
10. A message on the top portion of the TV screen “*saving data, please wait...*” will appear
11. Once the message disappears, click the **OK** button on the remote control

12. Click the right arrow key and look for your subscription channel list named **My Arab / My GMA / My Maghreb** to view all the channels

DANSAT PREMIUM/ DANSAT PREMIUM 2

1. Click the **MENU** button on the remote control
2. Press the right arrow key to select **Installation**
3. Scroll down and select **TP List**, then press **OK** on the remote control
4. Make sure satellite is set to **BADR 4/5/6**. If not, press the right arrow key and look for **BADR 4/5/6**
5. Scroll down the list, and select the frequency **11823MHz, 27500Ks/s, V** (*This frequency will allow you to get all My-HD Channels*)
6. Click the **OK** button the remote control and set the following:
 - 6.1 - **FTA Only** set to **NO** (*Default setting so no need to change*)
 - 6.2 - **Scan Channel** set to **TV + Radio** (*Default setting so no need to change*)
 - 6.3 - **Network Search** set to **YES**
7. Select the **OK** option to commence the scanning process
8. Click the **OK** option once the **"Search End"** message appears
9. Click the **EXIT** button four times on the remote control to set the TV screen back to full screen mode
10. Click the **OK** button on the remote control
11. Click the right arrow key and look for your subscription channel list named **My Arab / My GMA / My Maghreb** to view all the channels

ALTECH HDIR 1

1. Click on the **MENU** button on the remote control
2. Go to **Settings**
3. Go to **Installation**
4. Type in the pin code **0-0-0-0**, and then click the **OK** button on the remote
5. Select **Channel Search**
6. Select **Satellite**
7. Click the right arrow key on the remote and select **Arabsat BADR/4/5/6/7**
8. Set the **Network Search** option to **ON**
9. Click the **OK** button on the remote control to commence the scanning process
10. Once the scan is done, click the **Exit** button on the remote control to set the TV screen back to full screen mode
11. Click the **OK** button on the remote control to view the channel list on the left side of the screen
12. Click the right arrow key on the remote control and look for your subscription channel list named **My Arab / My GMA / My Maghreb** to view all the channels

My-HD COMPATIBLE HUMAX RECEIVER MODELS

(Includes: HD-Mini, IR3100HD, IR-Eco, IR-Free HD, I-Cord, & etc. /Excludes: IR4000HD)

1. Click the **MENU** button on the remote control
2. Go to **Settings**, and click **OK** on the remote
3. Go to **Installation**, and click **OK** on the remote
4. Type in the password/pin code **0-0-0-0**
5. Select **Search Channels**, and click **OK** on the remote

Important Note: Please make sure that if any other satellites are active, please go to the **Transponder** option of those other satellites, and select **NONE** to deactivate them temporarily

6. Click **OK** on the **ARABSAT/BADR** box
7. Scroll down and set the **Test Transponder** to **11938, V, 27500, 3/4** *(This frequency will allow you to get all channels from ARABSAT satellite)*
8. Scroll down and select the **OK** option, then click **OK** button on the remote
9. Click the **Transponder** box below ARABSAT/BADR and select **ALL**
10. Click the **Opt+** button on the remote control and set **Network Search ON**
11. Scroll down and select the **OK** option, and then click the **OK** button on the remote
12. Select the **Search** option, and click the **OK** button on the remote control to commence the scanning process
13. Click the **OK (Save)** button on the remote control to save the channels scanned
14. Select **YES**, and then press the **OK** button on the remote once the **"After saving the channels, do you want to Exit the Installation menu?"** message appears
15. Click the **OK** button on the remote and look for the My-HD channels under **TV list, HDTV list, or ARABSAT/BADR list**

HUMAX IR4000HD

1. Click the **MENU** button on the remote control
2. Go to **Settings**, and click **OK** on the remote
3. Go to **Search Channels**, and click **OK** on the remote
4. Type in the password/pin code **0-0-0-0**

Important Note: Please make sure that if any other satellites are active, please go to the **Transponder** option of those other satellites, and select **NONE** to deactivate them temporarily

5. Click **OK** on the **BADR 4&6** box
6. Scroll down and set the **Test Transponder** to **11938, V, 27500, A...** *(This frequency will allow you to get all channels from ARABSAT satellite)*

7. Scroll down and select the **OK** option, and then click **OK** button on the remote
8. Scroll down and click the **Transponder** box below BADR 4&6 and select **ALL**
9. Click the **“+”** button on the remote, and select **Search Option**
10. Set **Network Search** to **ON**
11. Scroll down and select the **OK** option, and then click the **OK** button on the remote
12. Scroll down and select the **Search** option, and then click the **OK** button on the remote to commence the scanning process
13. Click the **EXIT** button on the remote
14. Select **YES**, and then press the **OK** button on the remote once the ***“Do you want to save the channels searched upto this point?”*** message appears
15. Click the **EXIT** button on the remote to set the display to full screen mode
16. Click the **OK** button on the remote and look for the My-HD channels under **TV list or HDTV list**